CONTENUTO DELLA CONFEZIONE:

- 2 batterie
- 2 atomizzatore con punta a goccia
- 1 bottiglia con ago
- 1 caricabatteria USB con cavo
- 1 adattatore da parete
- 1 manuale d'uso

ISTRUZIONI PER L'USO

Per un uso sicuro ed efficace dell'atomizzatore, si prega di leggere attentamente le seguenti informazioni prima dell'uso dell'apparecchio e si prega di seguire le procedure operative standard.

ISTRUZIONI PER IL PRIMO USO

Rimuovere la batteria dalla scatola, avvitare il cavo del caricabatteria, collegare il cavo alla presa dell'adattatore e fare caricare per 8 ore. Si deve accendere la luce rossa, quando diventa verde il dispositivo sarà completamente caricato. Anche se la luce diventa verde prima delle 8 ore, si consiglia di aspettare fino alle 8 ore di carica per garantire un'ottima durata delle batterie. Le ricariche successive richiederanno un minor tempo di carica.

La batteria può essere attivata o disattivata premendo rapidamente il tasto 5 volte. L'atomizzatore si illuminerà quando è accesso. La batteria si può anche ricaricare con una presa USB. Non usare il caricatore in luoghi umidi. Non accendere l'alimentatore in prossimità di una fonte di alta temperatura. Non saldare o forare l'alimentatore

Se l'alimentatore fa un odore strano, si riscalda, si decolora, si deforma o presenta qualsiasi anomalia durante la carica, staccarlo dall'alimentazione e non utilizzarlo. Il caricabatteria dell'atomizzatore può essere utilizzato solo con il suo alimentatore dedicato. Non cercare di utilizzare questo caricabatteria con altri tipi di alimentatori. Tenere i componenti dell'atomizzatore ed il serbatoio lontani dalla portata dei bambini e degli animali.

SOSTITUZIONE DELL' ALIMENTATORE

La batteria deve essere ricaricata quando il kit non produce più vapore. Svitare la batteria dal kit ed inserire una batteria completamente carica per continuare a produrre vapore.

ALIMENTAZIONE

La tensione di alimentazione del caricatore USB per uso domestico é AC 100V-240V 50/60HZ. La tensione di alimentazione del caricabatteria USB per auto é DC 12V-24V. La tensione in entrata del caricabatteria USB é 5V.500mAh e la tensione in uscita è 4.2V 420mAh. Controllare che la tensione di rete corrisponda a quella richiesta dal caricatore. La batteria ha una durata di circa 300 ricariche. Una volta superato questo valore, la durata della ricarica diminuisce in modo significativo ed è necessario utilizzare una nuova batteria.

COME RICARICARE IL CE4

Estrarre la bottiglia con l'ago, svitare la parte superiore e riempire con il liquido. Sostituire il tappo con l'ago, estrarre e svitare l'ugello, forare la capsula del liquido sul bordo. Riempire il serbatoio almeno con 0,8 ml di liquido ma non superare 1,6 ml. Livellare l'atomizzatore e attendere un minuto.

UTILIZZO DELL' ATOMIZZATORE

Avvitare il CE4 riempito sulla batteria (non serrare eccessivamente). Tenere il dito sul pulsante, mentre inspirate il vapore. Rilasciare il pulsante quando allontanate l'atomizzatore dalle labbra. L'atomizzatore potrebbe danneggiarsi se il pulsante viene premuto troppo spesso senza inspirare. Non utilizzare l'atomizzatore in posizione verticale, perchè il liquido potrebbe fuoriuscire. Non premere il pulsante per più di 5 secondi per non surriscaldare l'atomizzatore. Se l'atomizzatore produce vapore in continuo o presenta segni di surriscaldamento, smettere di utilizzarlo ed aspettare circa 10 secondi. Dopo potete iniziare a riutilizzarlo

MANUTENZIONE

Effettuare la manutenzione dell'atomizzatore regolarmente. Non fate seccare completamente il CE4 prima di riempirlo con liquido. Pulire le filettature dei diversi componenti del CE4, dei caricabatterie e l'alimentatore utilizzando un panno imbevuto di alcol denaturato non profumato. Una filettatura pulita permette una migliore conduttività elettrica. Soffiare nel CE4 di tanto in tanto per eliminare il liquido residuo. Quando la fuoriuscita del vapore diminuisce in modo significativo, la batteria deve essere ricaricata.

SOSTITUZIONE DELL'ATOMIZZATORE

Durante l'uso dell'apparecchio se la batteria è completamente carica ma la fuoriuscita del vapore diminuisce notevolmente, è necessario sostituire il CE4. Svitare il CE4 dalla batteria e sostituirlo con il CE4 appena riempito.

CORRETTEZZA

L'atomizzatore non danneggia l'ambiente circostante e le persone, consigliamo comunque di chiedere cortesemente il permesso di utilizzarlo quando siete in un luogo pubblico.

ATTENZIONE

Non riconosciamo alcuna garanzia o risarcimento danni in caso di uso errato. Vi preghiamo di prendere nota che l'uso di altre cartucce o di liquidi diversi da quelli raccomandati può danneggiare il CE4 o il gruppo in modo irreparabile. Smaltire il vecchio alimentatore nei punti di raccolta differenziata presenti sul territorio.

REQUISITI DI SICUREZZA

1 • Spegnere sempre la batteria prima di riporla in borsa o in tasca per evitare che si accenda accidentalmente

2 • Rimuovere sempre la batteria dal caricabatteria quando il LED è verde

3 • NON lasciare la sigaretta elettronica in luoghi troppo caldi o umidi.

4 • NON far cadere la sigaretta elettronica, NON forzare la batteria, attenersi sempre alle istruzioni quando si ricarica il liquido.

Questo prodotto è un'alternativa all'uso delle tradizionali sigarette. Il prodotto NON deve essere considerato una terapia per smettere di fumare. Questo prodotto NON deve essere usato da persone che hanno dimostrato sensibilità alla nicotina, donne in gravidanza o in allattamento, persone con problemi cardiaci. L'uso dell'apparecchio non è destinato a persone (compresi i bambini) con ridotte capacità mentali. Non lasciare l'apparecchio incustodito in presenza di bambini.

SMOQUEEN
ispiria

WHATS IN THE BOX

- 2 batteries
- 2 cartomizer with drip tip
- 1 needle bottle
- 1 USB charger with lead
- 1 wall adaptor plug
- 1 user manual

INSTRUCTION MANUAL

For the safe and effective use of the atomizer, please read through the following information carefully before use and strictly follow standard operating procedures.

INSTRUCTIONS FOR FIRST TIME USE

Remove a battery from your box, screw into the charger lead, connect the lead to the adaptor plug and then charge it eight hours the first time. The light on the charging lead is red at first. It will turn green when fully charged after a normal charge. Even when the light turns green the first time you charge it, wait the 8 recommended hours to gain the best future performance of the battery's service life.
The subsequent charges of each battery will take much less. Turn battery on/off by rapidly pressing the button 5 times. Your atomizer will light up when it powers on. Please note batteries can also be charged using a USB port.

Do not use the charger in damp areas. Do not charge the power supply near a high-temp heat source. Do not weld or pierce the power supply. If you notice that the power supply emits any type of smell or heat or becomes discolored or deformed or shows any type of abnormality during charging, please cut off the power supply from the atomizer body or charger or stop using it.
The atomizer charger can be used only with its dedicated power supply. Do not try to use this charge with other kinds of power supply. Please keep atomizer components and tank atomizer away from children or pets.

POWER SUPPLY REPLACEMENT

The battery needs recharging when the kit no longer produces vapor. Unscrew the power supply battery from the kit and screw the fully charged one to continue vaporizing.

POWER SUPPLY

Input voltage of the USB home charger is AC 100V-240V 50/60HZ. The input voltage of the USB car charger is DC 12V-24V. The input voltage of the USB battery charger is 5V, 500mAh and the output voltage is 4.2V 420mAh. Be sure the local voltage complies with charger.
Atomizer power supply can charge about 300 times. After more than 300 charging cycles, the operating span lessens significantly and a new battery may be needed.

FILLING YOUR CE4

Remove your bottle with needle, unscrew the top & fill with e-juice. Replace the cap with the needle. Take out and unscrew the nozzle, pierce the e-liquid at the edge. Fill the tank not less than 0.8 ml but not more than 1.6 ml. Level your atomizer and wait one minute.

USING YOUR ATOMIZER

Screw the filled CE4 onto the battery (do not over tighten). Keep your finger on the button while inhaling the vapor. Release the button when you remove your atomizer from your lips. Pressing the button too often while not inhaling could damage it.

Do not use atomizer in a vertical position, since liquid could leak out. Do not press the manual button for more than 5 seconds to avoid overheating the atomizer. If the atomizer vaporizes continuously or shows signs of overheating, stop using it and wait about 10 seconds. Then you may continue.

Happy vaporizing!

MAINTENANCE

Maintain you atomizer on a regular basis.
Do not let the CE4 run completely dry before re-filling with e-juice. Clean the screw threads of the different parts such as CE4, chargers and power supply using tissue dipped in purified perfume-free alcohol (at your local drugstore). A clean screw thread will provide better electronic conduction.
Blow into the CE4 every now and then to evacuate left over liquid. When vapor diminishes significantly, this means the battery needs recharging.

ATOMIZER REPLACEMENT

When using this unit, if the battery is fully charged but you notice that vapor has decreased significantly this means that the CE4 may need to be replaced.
Unscrew the CE4 from the battery, and replace with the newly filled CE4.

COURTESY

Your atomizer does not cause any harm to people or the surrounding environment. However, we recommend, as an act of courtesy, to ask permission to use your atomizer in public places beforehand.

CAUTION

We do not accept any warranty or indemnity claims in case of wrong usage. Please be aware that using cartridges or liquids other than those recommended by atomizer may cause damage to the CE4 or unit, which may be beyond repair. Please dispose of the old power supply in your power supply recycling collection point.

SAFETY REQUIREMENTS

1 • Always remember to turn off the battery when you put it in your handbag or pocket to prevent it from switching on.

2 • Always remove it from the charger when the LED turns green.

3 • DO NOT leave your e cigarette in hot or damp places.

4 • DO NOT drop your e cigarette, DO NOT force the battery and always follow the instructions when refilling with liquid.

This product is an alternative to smoking traditional cigarettes. DO NOT consider this product as a therapy to quit smoking. This product should NOT be used by persons under the age of 18, nicotine-sensitive persons, pregnant or breastfeeding women or persons who are at risk of heart disease. This device should not be used by persons (children included) with reduced mental capacities. Children should be supervised to make sure they do not play with this device.

Importato e distribuito da/Imported and distributed by:
QUANTUM RETAIL S.r.l.
Via Milano, 1/b - 26016 Spino d'Adda (CR)
P.Iva 01391590195
Made in Prc

Vietato ai minori di 18 anni.
Forbidden to children under age 18.